TECHNICAL DATA

ACCESSORIES

DRIVERS CONSTANT CURRENT DRIVERS

INDIGO LIGHTING

22

155

35

PSMD3501324

- Dimmable constant current converter via phase start/end.

- Power voltage: 220-240 VAC.
- Minimum power in W: 13W.



CODE	Watt Max	PRI	SEC	INPUTS	OUTPUTS	Amb. T° Max.	L (mm)	l (mm)	H (mm)
PSMD3501324	13-24W	AC 230V	DC 350mA	1	1	45°C	155	35	22
Indoor use c	only.								
Protected ag of liquids.	gainst the ingress o	of solid bodies g	reater 12 mm. No	o protection agai	nst the ingress				
Live parts an insulation.	e equipped with a	dditional isolatio	n protection, suc	h as reinforced c	or double				
CE Product in c	onformity CE.								
The product	is dimmable.								

5 years warranty.